



Armonia Touch

Recommended daily production up to 200 cups





Drink	Cups per hour*
Espresso	150
Coffee/Cappuccino/Choco	120
Hot water	tot. 40 litres

^{*} the number of cups per hour may vary depending on drink size and setting









MODELS

LM Coffee Fresh Milk Instant



1 grinder



2 grinders



1 grinder+1 instant



2 grinders+1 instant 1 grinder+2 instants

EASY

Coffee Instant



1 grinder



1 grinder+1 instant



2 grinders+1 instant 1 grinder+2 instants

TECHNICAL DATA

Coffee hopper capacity	0.6 Kg
Instant container capacity	2.0
Coffee and steam boiler capacity	1.0 l each
Delivery spout range	95 - 155 mm
Coffee ground bin capacity	60 pcs
Net weight	LM: 42 Kg - EASY: 38 Kg
Gross weight	LM: 50 Kg - EASY: 46 Kg
Matching add-on units	Range A01

COLOURS

Front panel: white - Side and rear panels: white	00
Front panel: black - Side and rear panels: stainless steel	• •

DIMENSIONS



W 324 x D 560 x H 717 mm

VOLTAGE / TOTAL POWER

LM	EASY	
120V 1+N 50/60Hz 2.550W	120V 1+N 50/60Hz 1.350W	
200V 1+N 50/60Hz 3.114W	200V 1+N 50/60Hz 1.914W	
230V 1+N 50/60Hz 3.150W	230V 1+N 50/60Hz 1.950W	
240V 1+N 50/60Hz 3.160W	240V 1+N 50/60Hz 2.124W	

TECHNOLOGIES

















OPTION

MTT Milk Pump (LM only) to set the desired temperature for each milk-based drink and get a perfect foam	Hopper Lock to close the hoppers with a lock	
Coffee Hopper 1.1 Kg to maximize the capacity of the hopper to 1.1 Kg	Direct Coffee Ground Discharge to discharge coffee grounds directly into a bin placed under the machine	
Instant Container 3.0 I to maximize the capacity of the instant container to 3.0 I	Card Reader contactless transponder to read smart cards	
MaxSave to detect the presence/absence of users to reduce energy consumption	GSM System telemetry system to check machine data and revenues, as well as update	
Aroma Diffusion to spread a nice coffee aroma in the environment and remove steam	machine parameters via remote control	
inside the machine	Coin Box RM5	
Cup Positioning to place cups right under the delivery spout	coin box for self serve payments programmable for any currency, no change giver	